



Utilising proprietary LPRS easyRadio technology operating in the 434MHz Industrial Scientific & Medical (ISM) bands the Connect2Pi USB 'dongle' provides a simple 'wireless bridge' between Raspberry Pi (Pi2Pi), a Raspberry Pi and a PC or any other device that supports USB serial communications.

These devices provide considerably greater range and less power consumption than similar WiFi or Bluetooth dongles operating in the overcrowded 2.4GHz bands.

Frequency, bandwidth, power output and data rate can (optionally) be configured to allow multiple devices to communicate free from interference from each other and any other RF devices.

Features	Benefits
LPRS easyRadio RF Transceiver technology	Bi-directional link, no RF protocol software required
USB Connection	'Plug & Play' operation, appears as a 'Com' port
Low current consumption	Can be powered directly from Raspberry Pi
Integral SMA Antenna connector	Allows use of extension for optimal antenna position
FTDI FT232 USB IC	Linux & Windows drivers available (see below)
Transmit & Receive LEDs	Diagnostics
Configurable RF parameters (optional)	Fine tune for optimum performance
Up to 180 Bytes per packet	Ideal for 'Sense & Control' applications
Built-in Temperature Sensor	Usable by host program

Host devices can send and receive (half duplex) up to 180 Bytes of data per packet that will be seamlessly delivered and presented to other hosts within range. There is no need for any complicated 'bit balancing' or elaborate coding schemes. Easy: Data In and Data Out !

Specifications

Supply: +5V \pm 5%, Temperature 20°C

Parameter	Min	Typical /Default	Max	Units	Notes
Supply Voltage		5V		Volts	Powered by USB connection
Supply Current		25		mA	Receive (Idle state)
		35		mA	Transmit
USB Host Data Rate	2.4	19.2	115.2	Kbps	Configurable - See Note 1 below
Packet Size	1		180	Bytes	Auto detect end of packet
Frequency (Default)		434		MHz	Configurable
Receive Sensitivity		-107	-117	dBm	Configurable
RF Output Power	-5	+9	+10	dBm	Configurable
Antenna		50		Ω	Via SMA Connector
Range		200		m	Dependant on conditions/terrain
Operating Temperature	-40	20	85	°C	
Mechanical					
Size	80 x 22 x 10			mm	Including connectors, excluding antenna
Weight	11			g	Without antenna
USB Connector	USB Type A Plug				Cable not supplied

Notes

- 1) Parameters can be configured using 'easyRadio Companion' software available from: www.lprs.co.uk
- 2) Please read this datasheet in conjunction with the easyRadio Advanced datasheet available from www.lprs.co.uk
- 3) The device is supplied with a 434 MHz ¼ Wave whip Antenna

FTDI offers royalty-free virtual com port drivers for the following operating systems:

Windows 98, 98SE, ME, 2000, Server 2003, XP and Server 2008
 Windows 7 32,64-bit
 Windows XP and XP 64-bit
 Windows Vista and Vista 64-bit
 Windows XP Embedded Windows CE 4.2, 5.0 and 6.0
 Mac OS 8/9, OS-X
 Linux 2.4 and greater

LPRS Part Number: eRA-Connect2-Pi (Includes ERA400TRS transceiver)

Acknowledgements

Raspberry Pi is a trademark of the Raspberry Pi Foundation.

Terms and Conditions of Use

Low Power Radio Solutions Ltd has an on-going policy to improve the performance and reliability of their products; we therefore reserve the right to make changes without notice. The information contained in this data sheet is believed to be accurate however we do not assume any responsibility for errors or any liability arising from the application or use of any product or circuit described herein. This data sheet neither states nor implies warranty of any kind, including fitness for any particular application.

easyRadio modules are a component part of an end system product and should be treated as such. Testing to fitness is the sole responsibility of the manufacturer of the device into which easyRadio products are fitted, and is expected BEFORE deployment into the field.

Any liability from defect or malfunction is limited to the replacement of product ONLY, and does not include labour or other incurred corrective expenses.

Using or continuing to use these devices hereby binds the user to these terms.

Low Power Radio Solutions Ltd.
Two Rivers Industrial Estate
Station Lane
Witney
Oxon
OX28 4BH
England

Tel: +44 (0)1993 709418
Fax: +44 (0)1993 708575
Web: <http://www.lprs.co.uk>
Email: info@lprs.co.uk
Technical: technical@lprs.co.uk